



ENDRESS

Power Generators

ESE 604 DBG ES DIN

Order No. **151012KI**

Main features

Alternator type	Duplex
Continuous Power 3~ [kVA/kW]	6.5/5.2
Continuous Power 1~ [kVA/kW]	5.0/4.0
Nominal voltage [V]	400/230
Nominal Current [A]	8.7/21.7
Power factor cos (phi)	0,8
Frequency [Hz]	50
Protection Class [IP]	54

Engine

Engine Type	B&S Vanguard 16 HP
Design	2-cylinder. 4-stroke OHV
Displacement [ccm]	479
Output 3000 rpm	9,5
CO2 emissions [g / kWh]	927,21
CO2 test procedure	G1
Fuel	Petrol
Fuel tank capacity [l]	8,5
Fuel consumption @ 75% PRP [L/h]	2,4
Running time @ 75% PRP	3,5
Starting system	Electric starter
Sound power level LWA [db(A)]	97
Weight in kg ca.	117
Dimensions L x W x H [mm]	700 x 440 x 580
Shockproof sockets	3 x 230V 16A 1 x 400V CEE 16A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-11-9

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de



ESE 604 DBG ES DIN

Order No. 151012KI



Power Generators

Advantages at a glance

- Comprehensive functions, safe and simple operation
- DUPLEX current quality without compromise
- Fitted according to DIN 14685-1
- Multifunctional control display E-MCS 4.0 - a clear system
- Special equipment and accessories, available for many requirements
- Emergency start function over the recoil starter

Equipment features

- Insulation monitoring – without shut-off
- 3-way fuel cock for external refuelling
- Multifunction control display E-MCS 4.0
- Fuel level indicator over the E-MCS 4.0
- Lack of oil automatic switch-off
- Alternator overload protection
- Starter battery 12 V/20 A
- Folding handles
- Vehicle tool kit

Special equipment - not retrofittable

	Order No.
External start Nato socket	163 000
Charging current socket DIN 14690	163 010
Charging current socket MagCode	163 018
Automatic Choke	163 030
Insulation monitoring device with shut-off	163 071
Beos charging current socket	163 080
FireCAN	163 140
Remote start device	163 150
Special colour	auf Anfrage

Accessories

	Order No.
Exhaust hose (1.5 m)	163 120
Exhaust hose (2.5 m)	163 121
90° Adapter for Exhaust hose	163 130
Hose for refuelling without a canister	E100 592
Transport carriage for a 5 series DIN frame	163 101
Wheel Kit for the 5 and 8 series DIN frame with folding handle	163 103

garantía alguna ni implícita ni expresa del rendimiento de un motor concreto.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-11-9

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

