




ENDRESS

Power Generators

ESE 606 HS-GT

Order No. **112303**



Main features

Alternator type	synchron
Max. Output 1~ [kVA/kW]	7.2/6.4
Continuous Power 1~ [kVA/kW]	6.0/5.5
Nominal voltage [V]	230
Nominal Current [A]	26,1
Power factor cos (phi)	0,9
Frequency [Hz]	50
Protection Class [IP]	23

Engine

Engine Type	HONDA GX390 / 11 HP
Design	1-cylinder 4-stroke OHV
Displacement [ccm]	389
Output 3000 rpm	6,4
CO2 emissions [g / kWh]	743
CO2 test procedure	k.A
Fuel	Petrol
Fuel tank capacity [l]	30
Fuel consumption @ 75% PRP [L/h]	2,1
Running time @ 75% PRP	14,3
Starting system	Recoil starter
Sound power level LWA [db(A)]	97
Sound pressure level LPA (7 m) [db(A)]	72
Weight in kg ca.	77
Dimensions L x W x H [mm]	800 x 538 x 576
Shockproof sockets	1 x 230 V/16 A 1 x CEE 230 V/32 A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-4-24

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de



ESE 606 HS-GT

Order No. 112303



Power Generators

Equipment features

- Lack of oil automatic switch-off
- Alternator overload protection
- HONDA + Briggs & Stratton OHV engines
- Large fuel tank for long running times
- Compound regulated high performance generators for 400 V

Possible applications

- | | |
|---|-------|
| Electric tools up to | 230V |
| Gardening or construction equipment up to | 5400W |
| Compressors or pumps up to | 3600W |
| | 2800W |

Special equipment - not retrofittable

- | | Order No. |
|--|-----------|
| RCD protection switch incl. earthing kit | 162 009 |

Accessories

- | | Order No. |
|-----------------|-----------|
| Wheel kit | 161 000 |
| Maintenance kit | 164 029 |

garantía alguna ni implícita ni expresa del rendimiento de un motor concreto.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-4-24

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

