




ENDRESS

Power Generators

ESE 1306 DHS-GT ES

Order No. **230029**



Main features

Alternator type	synchron
Max. Output 3~ [kVA/kW]	13.2/10.5
Max. Output 1~ [kVA/kW]	7.6/6.8
Continuous Power 3~ [kVA/kW]	12.0/9.6
Continuous Power 1~ [kVA/kW]	6.9/6.2
Nominal voltage [V]	400/230
Nominal Current [A]	17,3/30
Power factor cos (phi)	0,8
Frequency [Hz]	50
Protection Class [IP]	23

Engine

Engine Type	HONDA GX630 / 21 HP
Design	2-cylinder 4-stroke OHV
Displacement [ccm]	688
Output 3000 rpm	12,4
CO2 emissions [g / kWh]	751
CO2 test procedure	k.A
Fuel	Petrol
Fuel tank capacity [l]	16
Fuel consumption @ 75% PRP [L/h]	4,2
Running time @ 75% PRP	3,7
Starting system	E-Start incl. battery
Sound power level LWA [db(A)]	102
Sound pressure level LPA (7 m) [db(A)]	77
Weight in kg ca.	137
Dimensions L x W x H [mm]	945 x 570 x 645
Shockproof sockets	1 x CEE 230 V/16 A 1 x CEE 400 V/16 A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-2-19

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de



ESE 1306 DHS-GT ES

Order No. 230029



Power Generators

Advantages at a glance

Does not conform to EU noise guideline 2000/14/EC

Equipment features

Lack of oil automatic switch-off

Alternator overload protection

HONDA + Briggs & Stratton OHV engines

Large fuel tank for long running times

Compound regulated high performance generators for 400 V

Possible applications

	400V	230V
Electric tools up to	9300W	6100W
Gardening or construction equipment up to	6200W	4100W
Compressors or pumps up to	4700W	3100W
Inverter welding equipment up to a dia. of 5.00 mm		

Special equipment - not retrofittable

	Order No.
Wireless remote control	162 007
RCD protection switch incl. earthing kit	162 009
3-way fuel valve	163 050

Accessories

	Order No.
Wheel kit	161 015
Wheel kit	161 015
Maintenance kit	164 032
Refueling system for 3-way fuel valve	163 110

выразить любую гарантию работы конкретного двигателя.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-2-19

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

